

Наименование			Светодиодный модуль											
			LINE 470X11.5 2X6 6W0.3A 2835	LINE 470X11.5 2X7 7W0.3A 2835	LINE 470X11.5 2X8 8W0.3A 2835	LINE 470X11.5 2X9 9W0.3A 2835	LINE 470X11.5 2X10 10W0.3A 2835	LINE 500X11.5 3X7 6.5W0.3A 2835	LINE 500X11.5 3X8 7.5W0.3A 2835	LINE 500X11.5 3X9 8.5W0.3A 2835	MODULE 145X43 2X6 24W0.7A 5050	MODULE 145X43 1X12 55W0.7A 5050	MODULE 234X57 8X8 32W0.7A 3030	
	I [mA]	U [V]												
Источник питания	ИПС25-350Т IP20 ОФИС 1610	350	35-72	2-3	2-3	2	2	2	2-3	2	2		1	1
	ИПС27-300Т IP20 ОФИС 1610	300	45-90	3-4	3	2-3	2	2	3-4	2-3	2	2	1	2
	ИПС30-350Т IP20 ОФИС 1610	350	40-84	3-4	3	2-3	2	2	3	2-3	2	2	1	1
	ИПС35-350Т IP20 3305	350	33-90	2-4	2-3	2-3	2	2	2-4	2-3	2-3	2	1	1-2
	ИПС50-350ТД (240-390) IP20 2010	240-390	50-140	4-6	3-5	3-5	2-4	3-4	4-6	3-5	3-4	2-4	1	2-3
	ИПС35-350ТУ IP20 0202	350	33-90	2-4	2-3	2-3	2	2	2-4	2-3	2-3	2	1	1-2
	ИПС50-350Т (90-140) IP67 3310	350	90-140	5-6	5	4-5	4	3-4	5-6	4-5	4-5	3-4		3
	ИПС60-700Т IP20 3310	700	27-85									1-2	1	1
	ИПС80-700Т IP67 3101	700	60-115									2-3	1	2

Приведены варианты последовательного подключения светодиодных модулей на один источник питания